


正六角形格子上の 1 : 2 共鳴

藤村 薫
鳥取大学工学部応用数理工学科
kaoru@damp.tottori-u.ac.jp

1


共鳴三角形による流れパターンの複雑化の例

C (Craik) - タイプ：2次元トルミーン・シュリヒティング波
からの3次元分化（ブラジウス境界層）



空間的共鳴

$$\psi(x, t) = \sum_j A_j(t) \phi_j(z) e^{i(k_j^x x + k_j^y y - \omega_j t)}$$




共鳴条件：

$$\sum_n p_n \mathbf{k}_n = 0 \text{ and } \sum_n p_n \omega_n = 0 \text{ for } \mathbf{k}_j = (k_j^x, k_j^y) \text{ and } p_n \in \mathbb{Z}$$

$|p_1| + |p_2| + |p_3| = 3$: 共鳴三角形

$$\begin{aligned} \dot{A}_1 &= \sigma_1 A_1 + \kappa_1 \bar{A}_2 \bar{A}_3 + O(|A_j|^3), \\ \dot{A}_2 &= \sigma_2 A_2 + \kappa_2 \bar{A}_3 \bar{A}_1 + O(|A_j|^3), \\ \dot{A}_3 &= \sigma_3 A_3 + \kappa_3 \bar{A}_1 \bar{A}_2 + O(|A_j|^3) \\ \sigma_n, \kappa_n &\in \mathbb{C} \end{aligned}$$

2



1:2 Hopf/定常モード相互作用


$$k_1^x = k_2^x, k_3^x = 2k_1^x, k_1^y = -k_2^y, \text{ and } k_3^y = 0, \omega_1 = -\omega_2 \text{ and } \omega_3 = 0 :$$

$$\dot{A}_1 = \sigma_1 A_1 + \kappa_1 \bar{A}_2 A_3 + O(|A_j|^3),$$

$$\dot{A}_2 = \bar{\sigma}_1 A_2 + \bar{\kappa}_1 A_3 \bar{A}_1 + O(|A_j|^3),$$

$$\dot{A}_3 = \sigma_3 A_3 + \kappa_3 A_1 A_2 + O(|A_j|^3)$$

$$\sigma_1, \kappa_1 \in \mathbb{C}, \sigma_3, \kappa_3 \in \mathbb{R}$$




1:2 定常モード間相互作用


$$k_1^x = k_2^x, k_3 = 2k_1, k_1^y = k_2^y = k_3^y = 0, \text{ and } \omega_1 = \omega_2 = \omega_3 = 0 :$$

$$\dot{A}_1 = \sigma_1 A_1 + \kappa_1 \bar{A}_1 A_2 + O(|A_j|^3),$$

$$\dot{A}_2 = \sigma_2 A_2 + \kappa_2 A_1^2 + O(|A_j|^3)$$

$$\sigma_1, \sigma_2, \kappa_1, \kappa_2 \in \mathbb{R}$$





$\zeta_1(t)$ と $\zeta_2(t)$ に対する方程式のもつ対称性: Γ

$$\frac{d}{dt}\zeta = g(\zeta, \lambda) \rightarrow \frac{d}{dt}(\gamma\zeta) = g(\gamma\zeta, \lambda) \text{ for all } \gamma \in \Gamma$$

$\Leftrightarrow g(\gamma\zeta, \lambda) = \gamma g(\zeta, \lambda) \text{ for all } \gamma \in \Gamma$: Γ - 同変性

Γ -不变実多項式 $f(\zeta)$:

$$f(\gamma\zeta) = f(\zeta) \text{ for all } \gamma \in \Gamma$$

Γ -同変ベクトル場によって生成された振幅方程式:


$$\frac{d}{dt}\zeta = g(\zeta, \lambda) = \sum_j f_j(\zeta)g_j(\zeta, \lambda)$$

5

O(2) 対称下での 1:2 定常モード相互作用


- 定常解の分類

- Dangelmayr, G. 1986 Steady state mode interactions in presence of O(2) symmetry. *Dyn. Stab. Syst.* **1**, 159–185.
- Buzano, E. & Russo, A. 1987 Bifurcation problems with O(2) \oplus Z₂ symmetry and the buckling of a cylindrical shell. *Annuli di Matematica Pura ed Applicata (IV)* **146**, 217–262.



O(2) 対称下での 1:2 定常モード相互作用

レイリー・ベナール問題



O(2) 対称下での 1:2 定常モード相互作用

- レイリー・ベナール問題における 1:2 定常モード相互作用

- Busse, F. H. & Or, A. C. 1986 Subharmonic and asymmetric convection rolls. *ZAMP* **37**, 608–623.
- Armbuster, D. 1987 O(2)-symmetric bifurcation theory for convection rolls. *Physica* **27D**, 433–439.
- Manogg, G. & Metzener, P. 1994 Strong resonance in two-dimensional non-Boussinesq convection. *Phys. Fluids* **6**, 2944–2955.
- Mercader, I., Prat, J. & Knobloch, E. 2001 The 1:2 mode interaction in Rayleigh-Bénard convection with weakly broken midplane symmetry. *Int. J. Bifurcation and Chaos* **11**, 27–41.
- Mercader, I., Prat, J. & Knobloch, E. 2002a The 1:2 mode interaction in Rayleigh-Bénard convection with and without Boussinesq symmetry. *Int. J. Bifurcation and Chaos* **12**, 281–308.

O(2) 対称性の下での 1:2 定常モード相互作用

$$\psi(x, t) = \zeta_1(t)\phi_1(z)e^{ik_0x} + \zeta_2(t)\phi_2(z)e^{2ik_0x} + c.c. + \dots$$

$\text{O}(2) = \text{SO}(2) \times \mathbb{Z}_2(\kappa)$

$\text{SO}(2): x \rightarrow x + d (\text{mod } 2\pi/k_0)$

$$\Leftrightarrow (\zeta_1, \zeta_2) \rightarrow (e^{i\theta}\zeta_1, e^{2i\theta}\zeta_2) \text{ for } 0 \leq \theta < 2\pi$$

$\mathbb{Z}_2(\kappa): x \rightarrow -x \Leftrightarrow (\zeta_1, \zeta_2) \rightarrow (\bar{\zeta}_1, \bar{\zeta}_2)$

$\text{O}(2)$ 不変多項式 :

$$\mathcal{P}_1 = \mathcal{P}_1(u, v, w, \lambda), \quad \mathcal{P}_2 = \mathcal{P}_2(u, v, w, \lambda)$$

$$\mathcal{Q}_1 = \mathcal{Q}_1(u, v, w, \lambda), \quad \mathcal{Q}_2 = \mathcal{Q}_2(u, v, w, \lambda)$$

$$u = |\zeta_1|^2, \quad v = |\zeta_2|^2, \quad w = \bar{\zeta}_1^2\zeta_2 + \zeta_1^2\bar{\zeta}_2$$

$\text{O}(2)$ -同変ベクトル場によって生成された振幅方程式 :

$$\dot{\zeta}_1 = \zeta_1 \mathcal{P}_1 + \bar{\zeta}_1 \zeta_2 \mathcal{Q}_1, \quad \dot{\zeta}_2 = \zeta_2 \mathcal{P}_2 + \zeta_1^2 \mathcal{Q}_2$$

9

定常解 $r_1 \neq 0, r_2 \neq 0$, and $\cos \Theta = \pm 1$: 混合モード

$$0 = \sigma_1 r_1 \pm \beta_1 r_1 r_2 + (\kappa_1 r_1^2 + \kappa_2 r_2^2) r_1,$$

$$0 = \sigma_2 r_2 \pm \beta_2 r_1^2 + (\kappa_3 r_1^2 + \kappa_4 r_2^2) r_2$$

定常解 $r_1 \neq 0, r_2 \neq 0$, and $\cos \Theta \neq \pm 1$: 伝播波

$$0 = \sigma_1 r_1 + \beta_1 r_1 r_2 \cos \Theta + (\kappa_1 r_1^2 + \kappa_2 r_2^2) r_1,$$

$$0 = \sigma_2 r_2 + \beta_2 r_1^2 \cos \Theta + (\kappa_3 r_1^2 + \kappa_4 r_2^2) r_2,$$

$$0 = \beta_2 r_1^2 r_2^{-1} + 2\beta_1 r_2$$

$$\theta_2 - 2\theta_1 = \Theta \neq n\pi$$

$$\dot{\theta}_1 = \beta_1 r_2 \sin \Theta \rightarrow \theta_1 = (\beta_1 r_2 \sin \Theta) t + \theta_1(0), \quad \theta_2 = 2\theta_1 + \Theta$$

$$\psi = r_1 \phi_1(z) e^{i(k_0 x + \theta_1)} + r_2 \phi_2(z) e^{2i(k_0 x + \theta_1 + \Theta)} + \dots$$

$$e^{i(k_0 x + \theta_1)} \propto e^{i\{k_0(x - [-k_0^{-1} \beta_1 r_2 \sin \Theta] \cdot t)\}}$$

11

Relative Equilibrium

原点におけるテイラー展開 :

$$\dot{\zeta}_1 = \sigma_1 \zeta_1 + \beta_1 \bar{\zeta}_1 \zeta_2 + (\kappa_1 |\zeta_1|^2 + \kappa_2 |\zeta_2|^2) \zeta_1,$$

$$\dot{\zeta}_2 = \sigma_2 \zeta_2 + \beta_2 \zeta_1^2 + (\kappa_3 |\zeta_1|^2 + \kappa_4 |\zeta_2|^2) \zeta_2$$

$$\zeta_1 = r_1(t) e^{i\theta_1(t)}, \quad \zeta_2 = r_2(t) e^{i\theta_2(t)}$$

$$\dot{r}_1 = \sigma_1 r_1 + \beta_1 r_1 r_2 \cos \Theta + (\kappa_1 r_1^2 + \kappa_2 r_2^2) r_1,$$

$$\dot{r}_2 = \sigma_2 r_2 + \beta_2 r_1^2 \cos \Theta + (\kappa_3 r_1^2 + \kappa_4 r_2^2) r_2,$$

$$\dot{\Theta} = -(\beta_2 r_1^2 r_2^{-1} + 2\beta_1 r_2) \sin \Theta$$

where $\Theta(t) = \theta_2(t) - 2\theta_1(t)$.

定常解 $r_1 = 0, r_2 \neq 0$: 単純モード

10

上下の反転対称性 \mathbb{Z}_2 : $(\zeta_1, \zeta_2) \rightarrow (-\zeta_1, -\zeta_2)$

$\text{O}(2) \oplus \mathbb{Z}_2$ -不変多項式 :

$$\mathcal{P}_1 = \mathcal{P}_1(u, v, w^2, \lambda), \quad \mathcal{P}_2 = \mathcal{P}_2(u, v, w^2, \lambda)$$

$$\mathcal{Q}_1 = \mathcal{Q}_1(u, v, w^2, \lambda), \quad \mathcal{Q}_2 = \mathcal{Q}_2(u, v, w^2, \lambda)$$

$$u = |\zeta_1|^2, \quad v = |\zeta_2|^2, \quad w = \bar{\zeta}_1^2 \zeta_2 + \zeta_1^2 \bar{\zeta}_2$$

$\text{O}(2) \oplus \mathbb{Z}_2$ -同変ベクトル場によって生成された振幅方程式 :

$$\dot{\zeta}_1 = \zeta_1 \mathcal{P}_1 + \bar{\zeta}_1 \zeta_2 w \mathcal{Q}_1, \quad \dot{\zeta}_2 = \zeta_2 \mathcal{P}_2 + \zeta_1^2 w \mathcal{Q}_2$$

原点におけるテイラー展開 :

$$\dot{\zeta}_1 = \sigma_1 \zeta_1 + (\kappa_1 u + \mu_1 v) \zeta_1 + \chi_1 \bar{\zeta}_1 \zeta_2 w + (\lambda_{11} u^2 + \lambda_{12} uv + \lambda_{13} v^2) \zeta_1,$$

$$\dot{\zeta}_2 = \sigma_2 \zeta_2 + (\kappa_2 u + \mu_2 v) \zeta_2 + \chi_2 \zeta_1^2 w + (\lambda_{21} u^2 + \lambda_{22} uv + \lambda_{23} v^2) \zeta_2$$

$\zeta_1 \neq 0, \zeta_2 = 0$: 大きなロール, $\zeta_1 = 0, \zeta_2 \neq 0$: 小さなロール

$\zeta_1 \neq 0, \zeta_2 \neq 0$: 混合ロール

12




Figure 1. Neutral stability curves for different Prandtl numbers, $P \rightarrow 0$, $P = 17.99491$, and 33.98985 . Solid curves denote the neutral curves for stationary modes while dashed curves denote those for travelling modes. Open circles denote parameter sets for 1:2 resonance, open squares denote those for 1:1:2 resonance, and open triangles denote those for 1:1:2:4 resonance.

13




Fig. 2. Linear neutral stability curves. The open circle indicates the parameter set at which the nonlinear degenerate situation occurs where the cubic coefficient of the Stuart-Landau equation (the first Landau constant) for a monochromatic mode vanishes. The closed circles denote the 1:2 interaction points.

14

O(2) 対称性の下での 1 : 2 共鳴による構 造安定なヘテロクリニック軌道

- Armbruster, Guckenheimer & Holmes, *Physica* 29D (1988) pp.257–282.

Proctor & Jones, *J.Fluid Mech.* 188 (1988) pp.301–355.

Porter & Knobloch, *Physica* 159D (2001) pp.125–154.

O(2) symmetric case under periodic boundary conditions.

$$\dot{z}_1 = \mu_1 z_1 + \alpha \bar{z}_1 z_2 + z_1 (d_{11}|z_1|^2 + d_{12}|Z_2|^2),$$

$$\dot{z}_2 = \mu_2 z_2 + \beta z_1^2 + z_2 (d_{21}|z_1|^2 + d_{22}|z_2|^2)$$

- Porter & Knobloch, *Physica* 201D (2005) pp.318–344.

Slightly broken symmetry: $O(2) \rightarrow SO(2)$

$$\dot{z}_1 = (\mu_1 + i\epsilon\omega_1) z_1 + \alpha \bar{z}_1 z_2 + z_1 (d_{11}|z_1|^2 + d_{12}|Z_2|^2),$$

$$\dot{z}_2 = (\mu_2 + i\epsilon\omega_2) z_2 + \beta z_1^2 + z_2 (d_{21}|z_1|^2 + d_{22}|z_2|^2)$$

15

O(2) 対称性の下での 1 : 2 共鳴による構 造安定なヘテロクリニック軌道

- Cox, *Physica* 95D (1996) pp.50–61.

A long-wave PDE model + amplitude equations under $O(2)$

$$\frac{\partial \theta}{\partial t} = -\alpha\theta - \frac{R-R_0}{R_0} \frac{\partial^2 \theta}{\partial x^2} - a \frac{\partial^4 \theta}{\partial x^4} + b \frac{\partial}{\partial x} \left(\frac{\partial \theta}{\partial x} \right)^3 + c \frac{\partial^2}{\partial x^2} \left(\frac{\partial \theta}{\partial x} \right)^2$$

- Mercader, Prat & Knobloch, *Int.J.Bifurcation and Chaos* 12 (2002) pp.2501–22.

Rayleigh-Bénard convection without midplane reflection symmetry.

- Nore, Moisy & Quartier, *Phys.Fluids* (2005) 17 064103.

von Kármán swirling flow, laboratory experiment

16

対称群によって互いに等値である C^r 級ベクトル空間において、構造安定なヘテロクリニックサイクルが存在。

Busse & Heikes: *Science* **208** (1980) pp.173–175, Guckenheimer & Holmes (1988): *Math. Proc. Camb. Phil. Soc.* (1988) **103** pp.189–192


$$\begin{aligned}\dot{x} &= x(l + ax^2 + by^2 + cz^2), \\ \dot{y} &= y(l + ay^2 + bz^2 + cx^2), \\ \dot{z} &= z(l + az^2 + bx^2 + cy^2).\end{aligned}$$

Theorem (Guckenheimer & Holmes):


In the space of one-parameter families of G -equivariant vector fields, there is an open set V with the following property: If $X_\lambda \in V$, then there is a bifurcation of the origin at $\lambda = \lambda_0$ such that

- (a) the origin loses stability as λ increases through λ_0
- (b) for $\lambda > \lambda_0$, there is a stable heteroclinic cycle near the origin.

17




19



Daumont, I., Kassner, K., Misbach, C. & Valance, A. 1997 Cellular self-propulsion of two-dimensional dissipative structures and spatial-period tripling Hopf bifurcation. *Phys. Rev. E* **55**, 6902–6906. (doi:10.1103/PhysRevE.55.6902)

18



20

問題設定 -- 2層 RB 問題




Proc. R. Soc. A (2008) 464, 133–153
doi:10.1098/rspa.2007.0168
Published online 23 October 2007

The 1 : 2 spatial resonance on a hexagonal lattice in two-layered Rayleigh–Bénard problems

BY K. FUJIMURA*

Department of Applied Mathematics and Physics, Tottori University,
Tottori 680-8552, Japan

21



1. Two-layered Rayleigh–Bénard problem

$$\begin{aligned} \rho_0^{(j)} \frac{D\vec{v}_j^*}{Dt^*} &= -\nabla^* p_j^* - \rho_0^{(j)} g [1 - \alpha_1^{(j)} (T_j^* - T_d) - \alpha_2^{(j)} (T_j^* - T_d)^2] \mathbf{e}_z + \mu_j \Delta^* \vec{v}_j^*, \\ \frac{DT_j^*}{Dt^*} &= \kappa_j \Delta^* T_j^*, \quad \nabla^* \cdot \vec{v}_j^* = 0, \quad (j = 1, 2). \end{aligned} \quad (1.1)$$

\mathbf{e}_z : the unit vector upward in the z -direction,

g : the acceleration due to the gravity,

μ_1, μ_2 : the viscous coefficients,

κ_1, κ_2 : the thermal diffusivities,

$\rho_0^{(1)}, \rho_0^{(2)}$: the densities.

physical properties: evaluated at $T_1^* = T_d$ and $T_2^* = T_d$.

2. Non-dimensionalization

$$t^* = \frac{d^2}{\kappa_1} t, \quad \vec{v}_j^* = \frac{\kappa_j}{d} \vec{v}_j, \quad \vec{x}^* = d \vec{x},$$

$$p_j^* = -d \rho_0^{(j)} g \int^z [1 - \alpha_1^{(1)} \tilde{D}_j (T^{(j)} - T_d) (1-z) - \alpha_2^{(j)} \tilde{D}_j^2 (T^{(j)} - T_d)^2 (1-z)^2] dz + \rho_0^{(j)} \frac{\kappa_j^2}{d^2} \pi_1,$$

$$T_j^* - T_d = (T^{(j)} - T_d) \tilde{D}_j [(1-z) + \theta_j(x, y, z; t)], \quad (j = 1, 2) \quad (2.1)$$

where we set $\tilde{D}_j = (-D)^{j-1}$, $T^{(1)} = T_b$, and $T^{(2)} = T_t$.

Assume $\kappa_1 = \kappa_2$ and $\bar{T} = 1 - z$. In the non-dimensional form:


$$\begin{aligned} P_j^{-1} \frac{D\vec{v}_j}{Dt} &= -P_j^{-1} \nabla \pi_j + R_j K_j \theta_j \mathbf{e}_z + R_j K_j \epsilon_j (2\bar{T}\theta_j + \theta_j^2) \mathbf{e}_z + \Delta \vec{v}_j, \\ \frac{D\theta_j}{Dt} - w_j &= \Delta \theta_j, \quad \nabla \cdot \vec{v}_j = 0, \quad (j = 1, 2), \quad \vec{v}_j = (u_j, v_j, w_j)^T \end{aligned} \quad (2.2)$$

where

$$R_j = \frac{\rho_0^{(j)} g \alpha_1^{(j)} (T^{(j)} - T_d) d^3}{\tilde{D}_j^3 \mu_1 \kappa_1}, \quad P_j = \frac{\nu_j}{\kappa_j}, \quad K_j = \tilde{D}_j^4, \quad \epsilon_j = \frac{\alpha_2^{(j)} (T^{(j)} - T_d) \tilde{D}_j}{\alpha_1^{(j)}}. \quad (2.3)$$

25

2層レイリー・ベナール問題に対する 中立曲線



27

3. Boundary conditions

$$\vec{v}_1 = \vec{v}_2 = 0 \quad \text{at } z = 0, 1, 1 + D^{-1}, \quad \theta_1 = \theta_2 = 0 \quad \text{at } z = 0, 1 + D^{-1}. \quad (3.1)$$


On the dividing plate, the temperatures need to satisfy

$$T_1^* = T_2^*, \quad \kappa_1 \frac{dT_1^*}{dz^*} = \kappa_2 \frac{dT_2^*}{dz^*} \quad \text{at } z^* = d, \quad (3.2)$$

which yield

$$\theta_1 = \frac{R_2}{R_1} \frac{D^4 \alpha_1^{(1)} \nu_2 \kappa_2}{\alpha_1^{(2)} \nu_1 \kappa_1} \theta_2 \equiv G \theta_2, \quad \frac{d\theta_1}{dz} = G \frac{d\theta_2}{dz} \quad \text{at } z = 1. \quad (3.3)$$

26



28

同変ベクトル場

$$\mathbf{z} = g(\mathbf{z}, \gamma)$$

$$\begin{aligned}\mathbf{z} &= (z_1(t), z_2(t), z_3(t), z_4(t), z_5(t), z_6(t)) \in \mathbb{C}^6 \\ \mathbf{g} &= (g_1(\mathbf{z}), g_2(\mathbf{z}), g_3(\mathbf{z}), g_4(\mathbf{z}), g_5(\mathbf{z}), g_6(\mathbf{z}))\end{aligned}$$

対称群 Γ の作用の下での同変性：

$$\mathbf{g}(\gamma \mathbf{z}) = \gamma \mathbf{g}(\mathbf{z}) \text{ for all } \gamma \in \Gamma$$

ここで、正六角形の持つ対称群： $\Gamma = D_6 \dot{+} T^2$

29

$R_{2\pi/3}$	$\mathbf{z} \rightarrow (z_2 z_3, z_1, z_5, z_6, z_4)$	$\Gamma = D_6 \dot{+} T^2$
c_v	$\mathbf{z} \rightarrow (z_1, z_3, z_2, z_4, z_6, z_5)$	
c	$\mathbf{z} \rightarrow (\bar{z}_1, \bar{z}_2, \bar{z}_3, \bar{z}_4, \bar{z}_5, \bar{z}_6)$	
$(s, t) \in T^2$	$\mathbf{z} \rightarrow (\mathrm{e}^{is} z_1, \mathrm{e}^{-i(s+t)} z_2, \mathrm{e}^{it} z_3, \mathrm{e}^{2is} z_4, \mathrm{e}^{-2i(s+t)} z_5, \mathrm{e}^{2it} z_6)$	

$$f(\gamma \mathbf{z}) = f(\mathbf{z}) \text{ for all } \gamma \in \Gamma$$




Figure A 1. Elements of closed polygons on a hexagonal lattice in the wavenumber plane. Short arrows denote wavevectors with k_c and long arrows denote wavevectors with $2k_c$. (a1): $|z_1|^2$, (a2): $|z_4|^2$, (a3): $\bar{z}_1^2 z_4$, (a4): $z_1 z_2 z_3$, (a5): $z_4 z_5 z_6$, (a6): $z_1^2 z_5 z_6$, (a7): $\bar{z}_1 z_2 z_3 z_4$, (a8): $z_2^2 z_3^2 z_4$, (a9): $z_1 \bar{z}_2 \bar{z}_3 z_5 z_6$. See (A 5).

30

Γ – equivariant polynomials $\mathbf{g}(\mathbf{z})$:

$$\mathbf{g}(\gamma \mathbf{z}) = \gamma \mathbf{g}(\mathbf{z}) \text{ for all } \gamma \in \Gamma$$

(b1) (b2) (b3) (b4) (b5) (b6) (b7) (b8) (b9) (b10) (b11) (b12)




Figure A 2. Open paths on a hexagonal lattice. Closed circles denote the starting point $(0, 0)$ and open circles denote the ending point $(k_c, 0)$. (b1): z_1 , (b2): $\bar{z}_1 z_4$, (b3): $\bar{z}_2 \bar{z}_3$, (b4): $\bar{z}_1 \bar{z}_5 \bar{z}_6$, (b5): $z_2 z_3 z_4$, (b6): $\bar{z}_2 z_3 \bar{z}_6$, (b7): $z_2 \bar{z}_3 \bar{z}_5$, (b8): $z_2 z_3 \bar{z}_5 \bar{z}_6$, (b9): $z_2 \bar{z}_3 z_4 z_6$, (b10): $z_2 z_3 z_4 z_5$, (b11): $\bar{z}_1 \bar{z}_2 \bar{z}_3 z_5$, (b12): $\bar{z}_1 \bar{z}_2 z_3 \bar{z}_6$. See (A 5).

Γ – equivariant polynomials $\mathbf{g}(\mathbf{z})$:

$$\mathbf{g}(\gamma \mathbf{z}) = \gamma \mathbf{g}(\mathbf{z}) \text{ for all } \gamma \in \Gamma$$




Figure A 3. Open paths on a hexagonal lattice. Closed circles denote the starting point $(0, 0)$ and open circles denote the ending point $(2k_c, 0)$. (c1): z_4 , (c2): z_1^2 , (c3): $\bar{z}_5 \bar{z}_6$, (c4): $z_1 \bar{z}_2 \bar{z}_3$, (c5): $\bar{z}_3 \bar{z}_5$, (c6): $\bar{z}_2 \bar{z}_6$, (c7): $z_1 \bar{z}_2 z_3 \bar{z}_6$, (c8): $z_1 z_2 \bar{z}_3 \bar{z}_5$, (c9): $\bar{z}_2 z_3^2$. See (A 5).

32

Amplitude equation generated by Γ – equivariant vector field

定常解

$$\dot{z}_j = g_j(z_1, z_2, z_3, z_4, z_5, z_6) \text{ for } 1 \leq j \leq 6$$



$$\begin{aligned} g_1(z) &= P_1 z_1 + P_2 z_1 z_4 + P_3 z_2 z_3 + P_4 z_1 z_5 z_6 + P_5 z_2 z_3 z_4 \\ &\quad + P_6(z_2 z_3 z_6 + z_2 z_3 z_5) + P_7(z_2 z_3 z_5 z_6 + z_2 z_3 z_4 z_6) \\ &\quad + P_8 z_2 z_3 z_4 z_5 + P_9(z_1 z_3^2 z_5 z + z_1 z_2^2 z_6) \\ g_4(z) &= Q_1 z_4 + Q_2 z_1^2 + Q_3 z_5 z_6 + Q_4 z_1 z_2 z_3 + Q_5(z_3^2 z_5 + z_2^2 z_6) \\ &\quad + Q_6 z_2^2 z_3^2 + Q_7(z_1 z_2 z_3 z_6 + z_1 z_2 z_3 z_5) \end{aligned}$$

P_j, Q_j : real functions of invariant polynomials

33

単純モード (正六角形): $(0,0,0,x,x,x)$, $x \in \mathbb{R}$ $D_6 + Z_2^2$
 $\{\mathcal{R}_{2\pi/3}, c, c_v, Z_2(\pi, 0), Z_2(0, \pi)\} \mathbb{R}\{(0,0,0,1,1,1)\}$

$$\sigma_2 + \delta_2 x + (\mu_{21} + 2\mu_{22})x^2 = 0$$




35

自明解: $(0,0,0,0,0,0)$ $D_6 + T^2$
 $\{\mathcal{R}_{2\pi/3}, c, c_v, S^1(\theta, 0), S^1(0, \theta)\}$

単純モード (ロール): $(0,0,0,x,0,0)$, $x \in \mathbb{R}$ $S^1 + Z_2^3$
 $\{c, c_v, Z_2(\pi, 0), S^1(0, \theta)\} \mathbb{R}\{(0,0,0,1,0,0)\}$

$$\sigma_2 + \mu_{21}x^2 = 0$$




34

混合モード (混合ロール): $(x,0,0,y,0,0)$, $x, y \in \mathbb{R}$ $S^1 + Z_2^2$
 $\{c, c_v, S^1(0, \theta)\} \mathbb{R}\{(1,0,0,0,0,0), (0,0,0,1,0,0)\}$

$$\sigma_1 + \beta_1 y + \kappa_{11}x^2 + \mu_{11}y^2 = 0,$$


$$\sigma_2 y + \beta_2 x^2 + \kappa_{21}x^2 y + \mu_{21}y^3 = 0$$



36

単純モード (長方形): $(0,0,0,x,y,y)$, $x \neq y \in \mathbb{R}$ \mathbb{Z}_2^4
 $\{c, c_v, \mathbb{Z}_2(\pi, 0), \mathbb{Z}_2(0, \pi)\} \mathbb{R}\{(0,0,0,1,0,0), (0,0,0,0,1,1)\}$

$$\sigma_2 x + \delta_2 y^2 + (\mu_{21}x^2 + 2\mu_{22}y^2)x = 0,$$

$$\sigma_2 + \delta_2 x + \mu_{22}x^2 + (\mu_{21} + \mu_{22})y^2 = 0$$



37

単純モード (三角形): $(0,0,0,z,z,z)$, $z \in \mathbb{C}$ $D_3 + \mathbb{Z}_2^2$
 $\{\mathbb{R}_{2\pi/3}, c_v, \mathbb{Z}_2(\pi, 0), \mathbb{Z}_2(0, \pi)\} \mathbb{C}\{(0,0,0,1,1,1)\}$

混合モード (長方形ロール): $(z,0,0,x,y,y)$, $z, x \neq y \in \mathbb{R}$ \mathbb{Z}_2^3
 $\{c, c_v, \mathbb{Z}_2(0, \pi)\} \mathbb{R}\{(1,0,0,0,0,0), (0,0,0,1,0,0)\}$

混合モード (混合三角形): (x,x,x,y,y,y) , $x, y \in \mathbb{C}$ D_3
 $\{\mathbb{R}_{2\pi/3}, c_v\} \mathbb{C}\{(1,1,1,0,0,0), (0,0,0,1,1,1)\}$

混合モード (混合長方形): (x,y,y,u,v,v) , $x \neq y, u \neq v \in \mathbb{R}$ \mathbb{Z}_2^2
 $\{c, c_v\} \mathbb{R}\{(1,0,0,0,0,0), (0,1,1,0,0,0)\}$




39

混合モード (混合六角形): (x,x,x,y,y,y) , $x, y \in \mathbb{R}$ D_6

$\{\mathbb{R}_{2\pi/3}, c, c_v\} \mathbb{R}\{(1,1,1,0,0,0), (0,0,0,1,1,1)\}$

$$\sigma_1 + \beta_1 y + \delta_1 x + (\kappa_{11} + 2\kappa_{12})x^2 + (\mu_{11} + 2\mu_{12} + \nu_1)y^2 + (2\eta_1 + \xi_1)xy = 0,$$

$$\sigma_2 y + \beta_2 x^2 + \delta_2 y^2 + (\kappa_{21} + 2\kappa_{22} + 2\xi_2)x^2y + (\mu_{21} + 2\mu_{22})y^3 + \nu_2 x^3 = 0$$



38

$\dot{z} = g(z, \lambda)$ の不動点 z_0 の軌道安定性

$$x_j = \operatorname{Re} z_j, \quad y_j = \operatorname{Im} z_j, \quad g_j^r = \operatorname{Re} g_j, \quad g_j^i = \operatorname{Im} g_j, \quad 1 \leq j \leq 6.$$

$$g(\gamma z) = \gamma g(z) \Rightarrow dg(\gamma z_0, \lambda) \gamma = \gamma dg(z_0, \lambda) \text{ for all } \gamma \in \Gamma.$$

$$\Leftrightarrow dg(z_0, \lambda) \sigma = \sigma dg(z_0, \lambda) \text{ for all } \sigma \in \Sigma_z$$

ここで Σ_z : 次で定義される固定化部分群

$$\Sigma_z = \{\sigma \in \Gamma : \sigma z = z\} \text{ for } z \in \mathbb{C}^6$$

$\gamma(\theta)$ を Γ において $\gamma(0) = 1$ を満たすなめらかな曲線であるとする。

$$g(z_0, \lambda) = 0 \text{ and } \gamma g(z) = g(\gamma z) \Rightarrow g(\gamma(\theta)z, \lambda) = 0$$

$$dg(z_0) \left(\frac{\partial \gamma}{\partial \theta} \right)_{\theta=0} z_0 = 0.$$

$$\Rightarrow \left(\frac{\partial \gamma}{\partial \theta} \right)_{\theta=0} z_0: \text{ゼロ固有値に属する } dg(z_0) \text{ の固有ベクトル}$$

40

例：正六角形に対する Jacobi 行列の固有値

$$\{R_{2\pi/3}, c, c_v\} + Z_2^2 :$$

$$\begin{pmatrix} a_{11} & a_{12} & a_{21} & a_{14} & a_{15} & a_{24} & b_{11} & b_{12} & b_{21} & b_{14} & b_{15} & b_{24} \\ a_{21} & a_{11} & a_{12} & a_{24} & a_{14} & a_{15} & b_{21} & b_{11} & b_{12} & b_{24} & b_{14} & b_{15} \\ a_{12} & a_{21} & a_{11} & a_{15} & a_{24} & a_{14} & b_{12} & b_{21} & b_{11} & b_{15} & b_{24} & b_{14} \\ a_{41} & a_{42} & a_{51} & a_{44} & a_{45} & a_{54} & b_{41} & b_{42} & b_{51} & b_{44} & b_{45} & b_{54} \\ a_{51} & a_{52} & a_{42} & a_{54} & a_{44} & a_{45} & b_{51} & b_{52} & b_{42} & b_{54} & b_{44} & b_{45} \\ a_{42} & a_{51} & a_{41} & a_{45} & a_{54} & a_{44} & b_{42} & b_{51} & b_{41} & b_{45} & b_{54} & b_{44} \\ c_{11} & c_{12} & c_{21} & c_{14} & c_{15} & c_{24} & d_{11} & d_{12} & d_{21} & d_{14} & d_{15} & d_{24} \\ c_{21} & c_{11} & c_{12} & c_{24} & c_{14} & c_{15} & d_{21} & d_{11} & d_{12} & d_{24} & d_{14} & d_{15} \\ c_{12} & c_{21} & c_{11} & c_{15} & c_{24} & c_{14} & d_{12} & d_{21} & d_{11} & d_{15} & d_{24} & d_{14} \\ c_{41} & c_{42} & c_{51} & c_{44} & c_{45} & c_{54} & d_{41} & d_{42} & d_{51} & d_{44} & d_{45} & d_{54} \\ c_{51} & c_{52} & c_{42} & c_{54} & c_{44} & c_{45} & d_{51} & d_{52} & d_{42} & d_{54} & d_{44} & d_{45} \\ c_{42} & c_{51} & c_{41} & c_{45} & c_{54} & c_{44} & d_{42} & d_{51} & d_{41} & d_{45} & d_{54} & d_{44} \end{pmatrix}$$

c :

$$\begin{pmatrix} a_{11} & a_{12} & a_{13} & a_{14} & a_{15} & a_{16} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{21} & a_{22} & a_{23} & a_{24} & a_{25} & a_{26} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{31} & a_{32} & a_{33} & a_{34} & a_{35} & a_{36} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{41} & a_{42} & a_{43} & a_{44} & a_{45} & a_{46} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{51} & a_{52} & a_{53} & a_{54} & a_{55} & a_{56} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{61} & a_{62} & a_{63} & a_{64} & a_{65} & a_{66} & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & d_{11} & d_{12} & d_{13} & d_{14} & d_{15} & d_{16} \\ 0 & 0 & 0 & 0 & 0 & 0 & d_{21} & d_{22} & d_{23} & d_{24} & d_{25} & d_{26} \\ 0 & 0 & 0 & 0 & 0 & 0 & d_{31} & d_{32} & d_{33} & d_{34} & d_{35} & d_{36} \\ 0 & 0 & 0 & 0 & 0 & 0 & d_{41} & d_{42} & d_{43} & d_{44} & d_{45} & d_{46} \\ 0 & 0 & 0 & 0 & 0 & 0 & d_{51} & d_{52} & d_{53} & d_{54} & d_{55} & d_{56} \\ 0 & 0 & 0 & 0 & 0 & 0 & d_{61} & d_{62} & d_{63} & d_{64} & d_{65} & d_{66} \end{pmatrix}$$

41

42

*R*_{2π/3} :

c_v :

$$\begin{pmatrix} a_{11} & a_{12} & a_{21} & a_{14} & a_{15} & a_{24} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{21} & a_{11} & a_{12} & a_{24} & a_{14} & a_{15} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{12} & a_{21} & a_{11} & a_{15} & a_{24} & a_{14} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{41} & a_{42} & a_{51} & a_{44} & a_{45} & a_{54} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{51} & a_{52} & a_{42} & a_{54} & a_{44} & a_{45} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{42} & a_{51} & a_{41} & a_{45} & a_{54} & a_{44} & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & d_{11} & d_{12} & d_{21} & d_{14} & d_{15} & d_{24} \\ 0 & 0 & 0 & 0 & 0 & 0 & d_{21} & d_{11} & d_{12} & d_{24} & d_{14} & d_{15} \\ 0 & 0 & 0 & 0 & 0 & 0 & d_{12} & d_{21} & d_{11} & d_{15} & d_{24} & d_{14} \\ 0 & 0 & 0 & 0 & 0 & 0 & d_{41} & d_{42} & d_{51} & d_{44} & d_{45} & d_{54} \\ 0 & 0 & 0 & 0 & 0 & 0 & d_{51} & d_{52} & d_{42} & d_{54} & d_{44} & d_{45} \\ 0 & 0 & 0 & 0 & 0 & 0 & d_{42} & d_{51} & d_{41} & d_{45} & d_{54} & d_{44} \end{pmatrix}$$

$$\begin{pmatrix} a_{11} & a_{12} & a_{12} & a_{14} & a_{15} & a_{15} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{21} & a_{11} & a_{12} & a_{24} & a_{14} & a_{24} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{21} & a_{12} & a_{11} & a_{24} & a_{24} & a_{14} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{41} & a_{42} & a_{42} & a_{44} & a_{45} & a_{45} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{51} & a_{52} & a_{42} & a_{54} & a_{44} & a_{45} & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{51} & a_{42} & a_{52} & a_{54} & a_{45} & a_{44} & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{11} & d_{12} & d_{12} & d_{14} & d_{15} \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{21} & d_{11} & d_{12} & d_{24} & d_{14} \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{21} & d_{12} & d_{11} & d_{24} & d_{14} \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{41} & d_{42} & d_{42} & d_{44} & d_{45} \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{51} & d_{52} & d_{42} & d_{54} & d_{44} \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{51} & d_{42} & d_{52} & d_{54} & d_{45} \end{pmatrix}$$

43

44

$Z_2(\pi, 0) :$

$$\begin{pmatrix} a_{11} & a_{12} & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ a_{21} & a_{11} & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & a_{11} & a_{24} & a_{24} & a_{14} & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & a_{42} & a_{44} & a_{45} & a_{45} & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & a_{42} & a_{45} & a_{44} & a_{45} & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & a_{52} & a_{45} & a_{45} & a_{44} & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & d_{11} & d_{12} & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & d_{21} & d_{11} & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{11} & d_{24} & d_{24} & d_{14} & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{42} & d_{44} & d_{45} & d_{45} & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{42} & d_{45} & d_{44} & d_{45} & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{52} & d_{45} & d_{45} & d_{44} & 0 \end{pmatrix}$$

45

$Z_2(0, \pi) :$

$$\begin{pmatrix} a_{11} & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & a_{11} & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & a_{11} & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & a_{44} & a_{45} & a_{45} & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & a_{45} & a_{44} & a_{45} & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & a_{45} & a_{45} & a_{44} & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & d_{11} & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{11} & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{11} & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{44} & d_{45} \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{45} & d_{44} \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{45} & d_{45} \end{pmatrix}$$

46

$$S^1(s, 0) = (e^{is}z_1, e^{-is}z_2, z_3, e^{2is}z_4, e^{-2is}z_5, z_6),$$

$$S^1(0, t) = (z_1, e^{-it}z_2, e^{it}z_3, z_4, e^{-2it}z_5, e^{2it}z_6)$$

$$\frac{\partial \rho(s, 0)}{\partial s} z = (iz_1, -iz_2, 0, 2iz_4, -2iz_5, 0) \Rightarrow (0, 0, 0, 0, 0, 0, 0, 0, 0, 1, -1, 0)$$

$$\frac{\partial \rho(0, t)}{\partial t} z = (0, -iz_2, z_3, 0, -2iz_5, 2iz_6) \Rightarrow (0, 0, 0, 0, 0, 0, 0, 0, 0, -1, 1)$$

$$(dg) \cdot \ker(dg) = 0$$

$$d_{44} - d_{45} = 0, \quad d_{45} - d_{44} = 0, \quad d_{45} - d_{45} = 0,$$

$$-d_{45} + d_{45} = 0, \quad -d_{44} + d_{45} = 0, \quad -d_{45} + d_{44} = 0$$

yields $d_{44} = d_{45}$.

47

$$\begin{pmatrix} a_{11} & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & a_{11} & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & a_{11} & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & a_{44} & a_{45} & a_{45} & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & a_{45} & a_{44} & a_{45} & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & a_{45} & a_{45} & a_{44} & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & d_{11} & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{11} & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{11} & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{44} & d_{44} \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{44} & d_{44} \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & d_{44} & d_{44} \end{pmatrix}$$

48

単純正六角形に対する固有値

$$\frac{\partial g_4^r}{\partial x_4} + 2 \frac{\partial g_4^r}{\partial x_5}, \quad 3 \frac{\partial g_4^i}{\partial y_4}, \quad 0(2), \quad \frac{\partial g_4^r}{\partial x_4} - \frac{\partial g_4^r}{\partial x_5}(2), \quad \frac{\partial g_1^r}{\partial x_1}(3) \text{ and } \frac{\partial g_1^i}{\partial y_1}(3)$$

単純口一ルに対する固有値

$$0, \quad \frac{\partial g_1^r}{\partial x_1}, \quad \frac{\partial g_1^i}{\partial y_1}, \quad \frac{\partial g_4^r}{\partial x_4}, \quad \frac{\partial g_5^r}{\partial x_5} + \frac{\partial g_5^r}{\partial x_6}(2), \quad \frac{\partial g_5^r}{\partial x_5} - \frac{\partial g_5^r}{\partial x_6}(2), \quad \text{and } \frac{\partial g_2^r}{\partial x_2}(4)$$

49

$\sigma^{(1)}$ に属する固有関数 $\psi^{(1)}(x, y, z)$ は以下に比例する：

$$e^{\pm ikx}, \quad e^{\pm ik(\frac{-1}{2}x + \frac{\sqrt{3}}{2}y)}, \quad e^{\pm ik(-\frac{1}{2}x - \frac{\sqrt{3}}{2}y)}, \\ e^{\pm 2ikx}, \quad e^{\pm 2ik(\frac{-1}{2}x + \frac{\sqrt{3}}{2}y)}, \quad e^{\pm 2ik(-\frac{1}{2}x - \frac{\sqrt{3}}{2}y)}$$

$$E_1 = e^{ikx}, \quad E_2 = e^{ik(\frac{-1}{2}x + \frac{\sqrt{3}}{2}y)}$$

とおき、 $\psi^{(j)}$ をフーリエ分解：

$$\psi^{(j)} = \sum_{m,n} \phi_{mn}^{(j)} E_1^m E_2^n.$$

$$L_{mn}(\mu) \phi_{mn}^{(j)} = \sigma_{mn}^{(j)} S_{mn} \phi_{mn}^{(j)},$$

$$S_{mn} = \mathcal{S}|_{\partial_x \rightarrow i(m - \frac{n}{2})\gamma, \partial_y \rightarrow i\frac{\sqrt{3}}{2}n\gamma, \partial_z \rightarrow d/dz'}$$

$$L_{mn} = \mathcal{L}|_{\partial_x \rightarrow i(m - \frac{n}{2})\gamma, \partial_y \rightarrow i\frac{\sqrt{3}}{2}n\gamma, \partial_z \rightarrow d/dz'}$$

51

$\psi(x, y, z, t)$ に対する非線形偏微分方程式：

$$\frac{\partial}{\partial t} \mathcal{S}\psi = \mathcal{L}(\mu)\psi + \mathcal{N}(\psi, \psi), \quad \mathcal{H}\psi = 0 \text{ on } \partial_D$$

$\mathcal{S}, \mathcal{L}, \mathcal{H}$: 線形作用素, \mathcal{N} : 2次の非線形項

線形固有値問題：

$$\mathcal{L}(\mu)\psi^{(j)}(x, y, z) = \sigma^{(j)} \mathcal{S}\psi^{(j)}(x, y, z), \quad j \geq 1.$$

$$\operatorname{Re} \sigma^{(1)} > \operatorname{Re} \sigma^{(2)} > \operatorname{Re} \sigma^{(3)} > \dots$$

$$\operatorname{Re} \sigma^{(1)} = 0, \quad \operatorname{Re} \sigma^{(j)} < 0 \text{ for } j \geq 2$$

を仮定すると ...

50

随伴問題：

$$\tilde{L}_{mn}(\mu) \tilde{\phi}_{mn}^{(j)} = \sigma_{mn}^{(j)} \tilde{S}_{mn} \tilde{\phi}_{mn},$$

with

$$\langle \tilde{\phi}_{mn}^{(j)}, (L_{mn}(\mu) - \sigma_{mn}^{(k)} S_{mn}) \phi_{mn}^{(k)} \rangle = \langle \phi_{mn}^{(j)}, (\tilde{L}_{mn}(\mu) - \sigma_{mn}^{(j)} \tilde{S}_{mn}) \tilde{\phi}_{mn}^{(j)} \rangle.$$

$$\psi(x, y, z, t) = \sum_{m=-\infty}^{\infty} \sum_{n=-\infty}^{\infty} \sum_{j=1}^{\infty} A_{mn}^{(j)}(t) \phi_{mn}^{(j)} E_1^m E_2^n, \quad A_{-m-n}^{(j)} = \bar{A}_{mn}^{(j)}$$

$$A_{mn}^{(j)} = \sigma_{mn}^{(j)}(\mu) A_{mn}^{(j)} + \sum_{k,l} \lambda_{k,l,m-k,n-l}^{(j,p,q)} A_{k,l}^{(p)} A_{m-k,n-l}^{(q)},$$


$$\sigma_{mn}^{(j)}(\mu) = \frac{\langle \tilde{\phi}_{mn}^{(j)}, L_{mn}(\mu) \phi_{mn}^{(j)} \rangle}{\langle \tilde{\phi}_{mn}^{(j)}, S_{mn} \phi_{mn}^{(j)} \rangle}, \quad \lambda_{k,l,m-k,n-l}^{(j,p,q)} = \frac{\langle \tilde{\phi}_{mn}^{(j)}, N(\phi_{kl}^{(p)}, \phi_{m-k,n-l}^{(q)}) \rangle}{\langle \tilde{\phi}_{mn}^{(j)}, S_{mn} \phi_{mn}^{(j)} \rangle}.$$

52

中心多様体低減

$$A_{mn}^{(j)} = h_{mn}^{(j)}(A_{\pm 1,0}^{(1)}, A_{0,\pm 1}^{(1)}, A_{\mp 1,\mp 1}^{(1)}, A_{\pm 2,0}^{(1)}, A_{0,\pm 2}^{(1)}, A_{\mp 2,\mp 2}^{(1)}).$$

$$h_{mn}^{(j)} = \sum_{k_1, k_2, l_1, l_2} \gamma_{k_1 k_2 l_1 l_2}^{(j)} A_{k_1, k_2}^{(1)} A_{l_1, l_2}^{(1)} + O(3).$$



49 12

53

$$\begin{aligned} \dot{z}_1 &= \sigma_1 z_1 + \delta_1 \bar{z}_2 \bar{z}_3 + \beta_1 \bar{z}_1 z_4 + [\kappa_{11}|z_1|^2 + \kappa_{12}(|z_2|^2 + |z_3|^2)]z_1 \\ &+ [\mu_{11}|z_4|^2 + \mu_{12}(|z_5|^2 + |z_6|^2)]z_1 + \nu_1 \bar{z}_1 \bar{z}_5 \bar{z}_6 + \xi_1 z_2 z_3 z_4 + \eta_1 (\bar{z}_2 z_3 \bar{z}_6 + z_2 \bar{z}_3 \bar{z}_5), \end{aligned}$$

$$\begin{aligned} \dot{z}_4 &= \sigma_2 z_4 + \delta_2 \bar{z}_5 \bar{z}_6 + \beta_2 z_1^2 + [\kappa_{21}|z_1|^2 + \kappa_{22}(|z_2|^2 + |z_3|^2)]z_4 \\ &+ [\mu_{21}|z_4|^2 + \mu_{22}(|z_5|^2 + |z_6|^2)]z_4 + \nu_2 z_1 \bar{z}_2 \bar{z}_3 + \xi_2 (\bar{z}_3^2 \bar{z}_5 + \bar{z}_2^2 \bar{z}_6). \end{aligned}$$

$$\gamma_{k_1 k_2 l_1 l_2}^{(j)} = \frac{\lambda_{k_1 k_2 l_1 l_2}^{(j11)}}{\sigma_{k_1 k_2}^{(1)} + \sigma_{l_1 l_2}^{(1)} - \sigma_{k_1 + k_2, l_1 + l_2}^{(j)}}$$

$$A_{10}^{(1)} \rightarrow z_1, A_{01}^{(1)} \rightarrow z_2, A_{-1-1}^{(1)} \rightarrow z_3,$$

$$A_{20}^{(1)} \rightarrow z_4, A_{02}^{(1)} \rightarrow z_5, \text{ and } A_{-2-2}^{(1)} \rightarrow z_6$$

54